

Single Channel, Power Monitor











Reads ALL Power Detectors Both thermopiles and photo detectors

Large LCD Display

- . 76 x 57 mm
- . 32 mm digits

Unique Ergonomic Design

Great for both handheld and tabletop use

Accurate

24 bit A/D converter for high resolution measurements

- **Single-Button Navigation** Direct access to all the functions
- **eXtremely Low Consumption** Lasts 670 hours with 4 AA alkaline batteries
- **Economical**

Get the best value for your money with this inexpensive and simple to use power monitor





Accessories

» External Power Supply 9 Volts power supply available in option.

» Protective Pouch

Protect your monitor from scratches and dust.



» Pelican Carrying Case

We offer a robust hard shell polymer carrying case.



UNO

SPECIFICATIONS

| Model | UNO |
|----------------------------------|--------------------------------------|
| | |
| Detector Types | Thermopiles, Photo Detectors |
| Display | LCD |
| POWER METER SPECIFICATIONS | UNO |
| Power Range | 5 pW to 10 kW |
| Thermopile | Single wide range scale |
| Photo Detector | Autoscale |
| Monitor Accuracy | ±1 % |
| Statistics | None |
| DETECTOR COMPATIBILITY | |
| Thermopiles | Average Power |
| Photo Detectors | Average Power (mW) |
| GENERAL SPECIFICATIONS | |
| Digital Display Size | 76 x 57 mm LCD |
| Digit Height | 32 mm |
| Digit Type | High Contrast Fields |
| Data Display | Real Time |
| Dimensions (Without Stand) | 210W x 122H x 44D mm |
| Weight (With Batteries) | 0.47 kg |
| Battery Type | 4 x AA Alkaline |
| Battery Life (Estimated) | 670 hours with detector |
| External Power Supply (Optional) | 100/240 VAC 50-60 Hz to 9 VDC 1.66 A |
| ORDERING INFORMATION | |
| Full Product Name | UNO |
| Product Number | 200982 |

Gentec-EO Worldwide



Leader in Laser Beam Measurement Since 1972

Headquarters

445 St-Jean-Baptiste, Suite 160 Québec, QC, G2E 5N7, CANADA

T (418) 651-8003 F (418) 651-1174 1.888.5Gentec (543.6832)

info@gentec-eo.com

Calibration Centers

Quebec City, Canada Olching (Munich), Germany